QUICK START GUIDE

USB 3.0 Dual 2K Universal Docking Station

WL-UG39DK4V

WAVLINK (@WavlinkOfficial)
WAVLINK SUPPORT (@WavlinkTechSupport)

A: Package Contents

1 x USB 3.0 Dual 2K Universal Docking Station
1 x USB 3.0 Cable
1 x DVI to VGA Adapter
1 x Quick Start Guide
1 x DC12V Certified Power Adapter
1 x Vertical Aluminum Alloy Stand Set

B: Overview and Hardware Installation

1. Headphone Output.
2. Microphone Input.
3. Gigabit LAN: Connect an Ethernet cable to Gigabit LAN port for high speed interface.

4. DVI: Connect DVI monitor with maximum resolution: 2048*1152.
5. HDMI: Connect HDMI monitor with maximum resolution: 2048*1152.
6. 4 x USB 2.0 ports: Fulfill all USB 2.0 devices such as scanner, digital camera, keyboard, mouse, printer.
7. Type A Port*2: Connect any USB 3.0 compatible devices, backward compatible with USB 2.0 and1.1 devices.
8. USB 3.0 IN: Connect the Universal Docking Station to an available USB 3.0 port on the Laptop, PC or others.
9. DC Power Jack: For DC Power Adapter plug in to the Universal Docking Station.

C: System Requirements

- Processor : Dual-core 2GHz+ CPU and 2GB RAM for best performance.
- Computer screen for use with the device.
- Requires supported Intel/AMD/NVIDIA main GPU and WDDM compatible driver (most recent systems meet this requirement).
- Ethernet port requires full-duplex network infrastructure.
- Updated USB 3.0 host controller drivers and graphics drivers suggested for best performance and compatibility.
- Windows XP(32-bit only)SP3/Vista/7/8/Mac OS X10.6 or latest.

Note: 64-bit Editions of XP are not supported.

Windows 10, 8.1, 7, and XP drivers can be automatically installed by Windows Update (with an existing Internet connection) or can be downloaded from www.wavlink.com.

D: Software Installation

Please refer to the link at the end of this manual
Windows Installation

1. Select Driver for Windows and then double-click the **Setup.exe** to launch the installation wizard.

2. Follow the on-screen instructions until the installation is completed. Then reboot the computer when prompted.

Installation for Mac OS

1. Download the latest driver for your mac OS system on wavlink website.
2. Locate the download folder and double-click the driver you just downloaded.
3. Double-click the "**Displaylink Software Installer.pkg**" file then this menu may show up (it depends on your security settings), click "**OK**" to proceed if it does.

4. Navigate to Applications and then open DisplayLink Manager.

5. Click the DisplayLink Manager application icon in the notification area to open the application window. This confirms that the software is installed and running properly.

6. Select "Launch automatically after logging-in" for the software to start automatically every time you log-in.
Note: this is not compulsory but recommended to save you from repeating step4 each time you login

7. Now connect peripherals using DisplayLink technology and navigate to your System Preferences to turn on Security & Privacy

8. Enable "Screen Recording" to allow the DisplayLink Manager application to capture pixels and send them to your USB peripheral:
8.1 Please select "Privacy"tab.
8.2 Navigate to "Screen Recording" in the list on the left.
8.3 Then tick the "Screen Recording" permission for DisplayLink Manager.

9. If you have enabled notifications from DisplayLink Manager, it will remind you to allow screen recording when it detects that this permission is missing.

10. The notification will also appear in the DisplayLink Manager window.

11. Because the new permissions will only take effect the next time you launch the app, macOS invites you to "quit and reopen." In Catalina 10.15.x, select "Sign Out Now". please accept.

12. Now that it has sufficient permissions, reopen the DisplayLink Manager from the application in the Finder. On mac OS Big Sur the application will automatically restart.

13. Your monitor is now working properly.

External Monitor Settings: Windows

Option 1: Extend Mode

1. Click the DisplayLink icon in the bottom right corner to open the DisplayLink Manager Menu.
2. Roll the mouse cursor USB 3.0 Dock to bring up the Manager Menu.
3. Select Extend
4. The monitor is now extended in the direction it was the last time the display was in this mode. For more control, select "**Extend To**" and choose one of the options. This turns the device into Extend Mode and places it to the Left/Right/Above/Below of the main monitor.

Option 2: Mirror Mode

1. Click the DisplayLink icon in the bottom right corner to open the DisplayLink Manager Menu.
2. Roll the mouse cursor over USB 3.0 Dock to bring up the Manager Menu.
3. Select Mirror.
4. The resolution, color depth, and refresh rate of the primaryscreen arecopied on to the monitor connected to the docking station.

External Monitor Settings: Mac OSX

Option 1: Extend Mode

1. Open "**System Preferences**" and click Displays
2. Click on "**Arrangement**" to change the position of the displays currently connected.

Option 2: Mirror Mode

1. Open "**System Preferences**" and click "**Displays**".

2. Click on "**Arrangement**". Click the box marked "**Mirror Displays**".

Note

1. Does not provide power to attached host laptop or tablet; the host system will still require its power cable/charger.
2. 2.4Ghz wireless devices such as wireless keyboard/mouse receivers. Bluetooth and WiFi adapters, may not work in the USB 3.0 ports on the dock. Connecting wireless devices to the USB 2.0 ports on the rear of the dock is recommended for best results. If the problem still occurs, a short USB2.0 extension cable to move the wireless device further from the dock will often resolve the issue.

Driver Download: www.wavlink.com/driver/
Technical support: support@wavlink.com

Laden die Treiber herunter: www.wavlink.com/driver/
Technischen Service: support@wavlink.com

ドライバーダウンロード: www.wavlink.com/driver/
技術サービス: support@wavlink.com

Descargar controladores: www.wavlink.com/driver/
Servicios técnicos: support@wavlink.com

Télécharger les pilotes: www.wavlink.com/driver/
Assistance technique:support@wavlink.com

Scaricare i driver: www.wavlink.com/driver/
Assistenza tecnica: support@wavlink.com

驱动下载: www.wavlink.com/cn/driver/
技术支持:support@wavlink.com

Thank you for purchasing WAVLINK product!

Official website: www.wavlink.com
Technical support: support@wavlink.com

UG39DK4说明书WAVLINK-E7
105G铜版纸，彩色印刷，双面印刷+风琴折
成品尺寸：80*130mm
展开尺寸：480*130mm