



QUICK START GUIDE USB-C Dual 4K Universal Docking Station



WAVLINK (@WavlinkOfficial)
WAVLINK SUPPORT (@WavlinkTechSupport)

WL-UG69DK7

REV.4

Safety Instructions

Keep this Quick Start Guide for future reference. Keep this equipment away from humidity. If any of the following situation arises, get the equipment checked by a service technician:

- The equipment has been exposed to moisture.
- The equipment has been dropped and damaged.
- The equipment has obvious sign of breakage.
- The equipment has not been working well or you cannot get it work according to Quick Start Guide.

Copyright Statement

No part of this publication may be reproduced in any form by any means without the prior written permission. Regardless of any direct acknowledgment elsewhere in the body of this document, WAVLINK hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders.

Disclaimer

Information in this document is subject to change without notice. The manufacturer does not make any representations or warranties (implied or otherwise) regarding the accuracy and completeness of this document and shall in no event be liable for any loss of profit or any commercial damage, including but not limited to special, incidental, consequential, or other damage.

WEEE Directive & Product Disposal

At the end of its serviceable life, this product should not be treated as household or general waste. It should be handed over to the applicable collection point for the recycling of electrical and electronic equipment, or returned to the supplier for disposal.

System Requirements

- Laptop or PC with USB 3.0 port(s)
- Windows 7/8/10 or later
- Mac OS X 10.8 or later
- Android v5.0 Lollipop or later

Overview


Front Panel

USB 3.0 port supports data transfer rate up to 5Gbps

Supports BC 1.2 fast charging

USB 3.0 port supports data transfer rate up to 5Gbps

4-Pole Audio Jack for connecting to the headset or microphone



01

Remark

In "Display 1 & 2", DisplayPort works priority if you connect both HDMI and DP to the monitor, therefore, please select only one of them at a time.

Rear Panel


USB 3.0 ports support data transfer rate up to 5Gbps

RJ45 Gigabit port provides secure & high-speed networks

Display 1: HDMI or DisplayPort, up to 4096 x 2160@60Hz

Display 2: HDMI or DisplayPort, up to 4096 x 2160@60Hz

Power port



02

Driver Installation

The UG69DK7 Docking Station is based on displaylink USB graphic technology, it requires installing displaylink driver found here: <https://www.synaptics.com/products/displaylink-graphics/downloads> https://www.wavlink.com/en_us/search.html?key=WL-UG69DK7&type=driver

Remark


If you encounter functional issues on Mac OS High Sierra 10.13 or later, please visit <https://support.displaylink.com/knowledgebase/articles/1188004> for reference.

Configuration

For Windows 10


1. Audio Setting

1) Right click the Displaylink icon and select "Audio Setup".




03

2) Select "Playback">"Speakers", "Recording">"Microphone" as the following pictures.



2. Video Setting

1) Right click at any spot on your desktop and select "Display settings", then choose either monitor 1 or 2.



04

2) Scroll down to the "Multiple displays", and select the mode in the drop-down list that is fit for your need.

- Duplicate desktop on 1 and 2
- Duplicate desktop on 1 and 3
- Extend desktop to this display


For Mac OS Users

1. Select "System Preferences" and choose "Displays".




2. Click on "Arrangement" to change the position of displays currently connected.

05



Extende Mode

3. To use the mirror mode, you have to mark the "Mirror Displays" box below the central icon.



Mirror Mode

06

Supported Resolutions

* 5120 x 2880@60Hz	1600 x 900@60Hz
4096 x 2160@60Hz	1440 x 900@60Hz
3840 x 2160@60Hz	1368 x 768@60Hz
2560 x 1600@60Hz	1360 x 768@60Hz
2560 x 1440@60Hz	1280 x 1024@60Hz
2048 x 1536@60Hz	1280 x 960@60Hz
2048 x 1280@60Hz	1280 x 800@60Hz
2048 x 1152@60Hz	1280 x 768@60Hz
2048 x 1080@60Hz	1280 x 720@60Hz
1920 x 1200@60Hz	1024 x 600@60Hz
1680 x 1050@60Hz	848 x 480@60Hz
1600 x 1200@60Hz	800 x 480@60Hz

* Uses both DisplayPort outputs.

07

Attention

2.4Ghz wireless devices (such as wireless keyboard/mouse receivers, Bluetooth and WiFi adapter) may not work in the USB3.0 ports. That should be caused by the USB3.0 interface. Please try to use the USB 2.0 extension cable/hub to keep the wireless receiver/adaptor away from the docking.

Does not provide power attached to host laptop or tablet: the host system will still require its power cable/charger.

Official Website: www.wavlink.com
Technical Support: support@wavlink.com

08

UG69DK7说明书WAVLINK-E4
105G铜版纸, 彩色印刷, 双面印刷+折叠
成品尺寸: 75*110mm
展开尺寸: 375*110mm