



QUICK START GUIDE USB 3.0 to HDMI 2K Adapter



www.wavlink.com/en_us/WL-UG3501H
Scan the QR code or load the link for Quick Start Guide and Driver downloading

WL-UG3501H WAVLINK (@WavlinkOfficial)
WAVLINK SUPPORT (@Wavlink TechSupport)

Overview



- 1 LED indicator: Indicates the working status.
- 2 HDMI: Supports resolutions up to 2K(2560 x 1440)@50Hz.
- 3 USB 3.0: Provides data transfer rate up to 5Gbps.
- 4 Pole phone jack: Connects to the microphone.
- 5 Earphone port: Connects to the headset.

Features

- Turn any monitor, projector or HDMI compatible HDTV into a USB connected display.
- HDMI port provides images with high resolution up to 2560 x 1440@50Hz.
- USB3.0 port offers flexible connectivity with maximum 5Gbps data transfer.
- Expandable up to 6 display units.
- Supports extended and mirror modes.

01

In the Box

- 1 x USB 3.0 to HDMI 2K Adapter
- 1 x HDMI to DVI Adapter
- 1 x Quick Start Guide

System Requirement

- Windows 7, 8, 10 or later
- Mac OS X 10.11 or later

Driver Installation



To download the latest driver, please visit our official website: www.wavlink.com. Choose **SUPPORT > Driver > USB DISPLAY** and find the corresponding model. Generally speaking, the Win 10 system is driver-free for this adapter, but you may need to install the latest driver manually if the computer doesn't install the driver automatically.



02


To install the driver on Windows.

1. Click "install" and wait for the progress.




03

2. Click "Finish", now the driver is installed on your PC/laptop.





To install the driver on Mac

Download the driver from official website and install the driver according to the guide.



04




05

Display Mode Setting

For Windows Users

1. Right-click at any spot on your desktop and select "Display settings".




2. In section "Display", please select either monitor 1 or monitor 2.



06

3. Scroll down to the "Multiple displays", and select the mode in the drop-down list that is fit for your need.

Multiple displays




For MacOS Users

1. Select "System Preferences" and choose "Displays".




07

2. Click on "Arrangement" to change the position of displays currently connected.



Extend Mode

3. To use the mirror mode, you have to mark the "Mirror Displays" box below the central icon.



Mirror Mode

08

07 Supported Resolutions

2560 x 1440@50Hz	1360 x 768@60Hz
2048 x 1152@60Hz	1280 x 1024@60Hz
2048 x 1080@60Hz	1280 x 960@60Hz
1920 x 1200@60Hz	1280 x 800@60Hz
1920 x 1080@60Hz	1280 x 768@60Hz
1680 x 1050@60Hz	1280 x 720@60Hz
1600 x 1200@60Hz	1152 x 870@60Hz
1600 x 900@60Hz	1152 x 864@60Hz
1440 x 900@60Hz	1024 x 768@60Hz
1400 x 1050@60Hz	1024 x 600@60Hz
1368 x 768@60Hz	848 x 480@60Hz
1366 x 768@60Hz	

Official website: www.wavlink.com
Technical support: support@wavlink.com

09

UG3501H说明书WAVLINK-E5
105G铜版纸彩色双面印刷，风琴折
成品尺寸：85x125mm
展开尺寸：340x125mm
设计：吴钊竞 更换LOGO