



## QUICK START GUIDE

### USB 3.0 to HDMI Dual Display Adapter



WAVLINK (@WavlinkOfficial)  
WAVLINK SUPPORT (@WavlinkTechSupport)

WL-UG7602HC

**Safety Instructions**  
Always read the safety instructions carefully. Keep this Quick Start Guide for future reference. Keep this equipment away from humidity. If any of the following situation arises, get the equipment checked by a service technician:

- The equipment has been exposed to moisture.
- The equipment has been dropped and damaged.
- The equipment has obvious sign of breakage.
- The equipment has not been working well or you cannot get it work according to user's manual.

**Copyright Statement**  
No part of this publication may be reproduced in any form by any means without the prior written permission. Other trademarks or brand names mentioned herein are trademarks or registered trademarks of their respective companies.

**Disclaimer**  
Information in this document is subject to change without notice. The manufacturer does not make any representations or warranties (implied or otherwise) regarding the accuracy and completeness of this document and shall in no event be liable for any loss of profit or any commercial damage, including but not limited to special, incidental, consequential, or other damage.

**WEEE Directive & Product Disposal**

At the end of its serviceable life, this product should not be treated as household or general waste. It should be handed over to the applicable collection point for the recycling of electrical and electronic equipment, or returned to the supplier for disposal.

**01 Introduction**  
The USB3.0 to HDMI adapter is a multi-mode adapter that supports two HDMI video outputs; it can extend your image/video to an external display such as the projector, HDTV, or HDMI-based monitor. Whether you need to extend for work, stock market, gaming, or conference, this adapter is of great help to assist you with your task.

**02 Features**

- The compact and portable design makes it easy to carry around.
- USB 3.0 port and strong powerful GPU ensure the stable video transmission.
- One HDMI port supports 3840x2160/30Hz output and the other is 1920x1080/60Hz display output.
- Resolution supports from 640x480/60Hz up to 3840x2160/30Hz.
- Connects multiple USB 3.0 display adapters to your PC to extend your screen up to extra displays; windows up to 8 displays, Mac OS up to 6.
- Supports video decoder multiple formats (H.264, H.263, MP4, MP2, DivX, AVS, JPEG and etc).

**03 System requirement**


- Microsoft windows 7/8/8.1/10 or higher
- Mac OS 10.10.x or higher
- CPU Processor: Core i5 or higher
- RAM: 4GB
- Monitor supports 4K UHD

**04 In the box**

- 1 x USB 3.0 to HDMI Dual Display Adapter
- 1 x CD-shaped card for driver download links
- 1 x Quick Start Guide


**05 Display resolution**



		HDMI 2K	HDMI 4K
Win 10	Duplicate	1920*1080/60Hz	1920*1080/60Hz
	Extended	1920*1080/60Hz	3840*2160/30Hz
Mac OS	Duplicate	1920*1080/60Hz	3840*2160/30Hz
	Extended	1920*1080/60Hz	3840*2160/30Hz



**06 Driver Installation**

- To download the latest drivers, please visit WAVLINK website [https://www.wavlink.com/en\\_us/drivers/3dea44705bc1.html](https://www.wavlink.com/en_us/drivers/3dea44705bc1.html) and find the corresponding model.
- Click on the "exe" file to start the installing process.







- Click the "REBOOT" button to reboot the computer and finish the installation.

**07 Display Mode Setting**

**For Windows Users**


- Right-click at any spot on your desktop and select "Display settings".



- In section "Display", please select either monitor 1 or monitor 2.



- Scroll down to the "Multiple displays", and select the mode in the drop-down list that is fit for your need.




**For Mac Users**


- Select "System Preferences" and choose "Displays".



- Click on "Arrangement" to change the position of displays currently connected.




- To use the mirror mode, you have to mark the "Mirror Displays" box below the central icon.



**Notice:**  
Due to privacy policy applied in Mac, you may experience the following issue:



Select "System Preferences" and choose "Security & Privacy". Click on "Open Anyway" to agree the driver installation.



**08 Supported resolution**

HDMI 2K		HDMI 4K	
<b>Windows 10</b>		<b>Windows 10</b>	
1920x1080	60Hz	3840x2160	30Hz
1680x1050	60Hz	2560x1440	60Hz
1600x1200	60Hz	1920x1080	60Hz
1600x900	60Hz	1680x1050	60Hz
1440x1050	60Hz	1600x1200	60Hz
1440x900	60Hz	1600x900	60Hz
1280x1024	60Hz	1440x1050	60Hz
1280x800	60Hz	1440x900	60Hz
1280x720	60Hz	1280x1024	60Hz
1152x864	60Hz	1280x800	60Hz
1024x768	60Hz	1280x720	60Hz
800x600	60Hz	1152x864	60Hz
720x480	60Hz	1024x768	60Hz
640x480	60Hz	800x600	60Hz
		720x480	60Hz
		640x480	60Hz
<b>Mac OSX</b>		<b>Mac OSX</b>	
1920x1080	60Hz	3840x2160	30Hz
1920x1080	30Hz	2560x1440	60Hz
1600x900	60Hz	1920x1080	60Hz
1280x720	60Hz	1920x1080	30Hz
		1600x900	60Hz
		1280x720	60Hz

The exact list of supported resolutions depends on your monitor performance.  
Official website: [www.wavlink.com](http://www.wavlink.com)  
Technical support: [support@wavlink.com](mailto:support@wavlink.com)

# UG7602HC说明书WAVLINK-E1

105G铜版纸, 彩色印刷, 表面过油, 双面印刷+折叠

成品尺寸: 75\*110mm

展开尺寸: 450\*110mm